AC Current Transducer CVI 500S

Transducer for the electronic measurement of AC sinusoidal waveforms, with galvanic isolation between the primary (High power) and the secondary circuit (Electronic circuit).

 I_{PN} =5-15-30-50A



LEAD FREE



• Operating performances (AT =25 $^{\circ}$ C)

• operating perioritians () in		/	
Primary current	I _{PN}	0~5/15/30/50	Α
Output signal	I _{OUT}	4~20	mA/dc
Supply voltage (±5%)	V _{CC}	18-35	Vdc
Load resistance	R_L	<250	Ω
Accuracy (40%100% Primary current)	ϵ_{L}	±2	%
RMS Isolation voltage test, 50Hz,1min	Χ	2	KV
Frequency bandwidth	f	50-60	Hz

General data

Operating temperature	To	-25∼+70℃	
Storage temperature	T_S	-40∼+80℃	
Operating Humidity		0 - 95	% RH
Storage Humidity (Non-Condensing)		0 - 98	% RH
Mass	m	120g	
Note		Insulated plastic case recognized according to UL 94-V0	

Features

◆AC sinusoidal measurement	◆Panel mounting	
◆Average responding	♦Voltage output	


Applications

◆ Automation systems	Analog current reading for remote monitoring(e.g.motor) .
◆Panel meters	Simple connection displays power consumption.

Advantages

◆Easy to mount	◆High isolation between primary and secondary circuits
V = 0.0 y 10 0 0	, 2

T.H www.thic.net



No. 8 DongHuan 4th St. Chuang Ye 1st Rd. Jitigang, No.19,Lane428,Sec.2,Chung Shan Rd, HuKou Hsinchu,Taiwan R.O.C HuangJiang Town. Dongguan City. Guang Dong. China Tel:+886-35994440 Fax:+886-3-5902243
Tel:+86-769-83367090 Fax:+86-769-83367590 E:mail:fp@thic.net

T.H www.thic.net